

(19)



Europäisches Patentamt

European Patent Office

Office européen des brevets



(11)

EP 1 098 431 A1

(12)

EUROPEAN PATENT APPLICATION

published in accordance with Art. 158(3) EPC

(43) Date of publication:

09.05.2001 Bulletin 2001/19

(51) Int. Cl.⁷: H02P 6/16

(21) Application number: 99926965.7

(86) International application number:

PCT/JP99/03658

(22) Date of filing: 06.07.1999

(87) International publication number:

WO 00/04630 (27.01.2000 Gazette 2000/04)

(84) Designated Contracting States:

AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU
MC NL PT SE

(30) Priority: 15.07.1998 JP 20007998

(71) Applicant: Hitachi, Ltd.

Chiyoda-ku, Tokyo 101-8010 (JP)

(72) Inventors:

- KAWABATA, Yukio
Hitachi-shi, Ibaraki 319-1221 (JP)
- NOTOHARA, Yasuo
Hitachi-shi, Ibaraki 319-1221 (JP)

• TAHARA, Kazuo

Hitachi-shi, Ibaraki 319-1221 (JP)

• TAKAKURA, Yuhachi

Shimotsuga-gun, Tochì 329-4404 (JP)

• ISHII, Makoto

Shimotsuga-gun, Tochì 329-4404 (JP)

• SHINOZAKI, Hiroshi

Shimotsuga-gun, Tochì 329-4404 (JP)

(74) Representative:

Beetz & Partner

Patentanwälte

Steinsdorfstrasse 10


80538 München (DE)

(54) BRUSHLESS MOTOR CONTROL DEVICE AND EQUIPMENT USING THE CONTROL DEVICE

(57) The present invention supplies a position detection circuit, and a motor controller, that can not only obtain rotor position detection signals properly over the entire PWM control region, but also obtain these signals properly during PAM control. In a brushless motor controller based on the present invention to detect the magnetic pole position of the stator in the motor in accordance with the stator coil terminal voltages of multiple phases and control the energization of the stator coils, the comparison result information signal, after

being obtained through comparison between the detected voltage values corresponding to the foregoing terminal voltages, and a reference voltage value, is directly entered into control circuits, then the position of the rotor in the motor is properly detected immediately after power-on switching, without a rotor position detection inhibition time interval being provided, and the motor is controlled properly.

FIG. 1



EP 1 098 431 A1

Description

[Technical Field]

[0001] The present invention relates to a controller that controls the rotational speed of a brushless motor to the desired speed, and to an air conditioner that conditions interior air by controlling its internal compressor/blower driving brushless motor using this controller, a refrigerator that provides refrigeration by controlling its internal compressor/blower driving brushless motor using the controller, a washing machine that washes clothes by controlling its pulsator or spin-basket driving brushless motor using the controller, and a vacuum cleaner that cleans rooms by controlling its blower driving brushless motor using the controller.

[Prior Art]

[0002] Because of their easy maintenance, brushless motors each made of a combination of a permanent magnet rotor and stator coils are used in air conditioners, refrigerators, washing machines, and the like.

[0003] Brushless motor driving control requires close linking between the magnetic pole position of the rotor and the positions of the stator coils. The sensorless position detection scheme utilizing the counter-electromotive force induced into the stator coils by their interactions with the magnetic pole of the rotor is employed to detect the magnetic pole position of the rotor; it is not detected using a rotor position detection sensor such as a Hall element.

[0004] Brushless motor drives using the sensorless position detection scheme include those set forth in, for example, Japanese Application Patent Laid-Open Publication No. Hei-6-284783 and Hei-6-98583. For these brushless motor drives so designed as to detect the crossing point (namely, the rising or falling edge) between the terminal voltages of the motor and a reference voltage, the required electrical angle (for example, 15 degrees) is calculated in one way or another immediately after commutation so that a spike voltage signal will not be detected as a rotor position detection signal, and the time corresponding to this electrical angle is set as a position detection inhibition interval. During this inhibition interval, signal detection is inhibited, and signals are acquired only after the elapse of the inhibition time. Or the crossing point (namely, the rising or falling edge) with respect to the reference voltage is detected by modifying the pattern of chopping only the upper and lower switching devices among all six switching devices, and motor control is based on the detection position.

[0005] For the conventional brushless motor drives, since the required electrical angle must be calculated in one way or another immediately after commutation, the use of a microcomputer or the like to calculate this angle increases the processing time required, or the use of an

external circuit to perform the calculation requires complex circuit composition.

[0006] In the case of these conventional brushless motor drives, although mis-judgment based on the spike voltage developed during the inhibition interval can be prevented by providing the inhibition interval, if an abrupt load change causes output of a rotor position detection signal during the inhibition interval immediately after commutation, this signal cannot be detected. For this reason, there arises the trouble that since a position significantly offset from the actual position of the rotor is likely to be mis-judged as the actual rotor position, operation becomes unstable or the motor decreases in operational efficiency or steps out.

[0007] An object of the present invention is to supply a brushless motor controller that can properly detect the position of a rotor immediately after commutation, without being provided with a position detection inhibition interval immediately after commutation.

[0008] Another object of the present invention is to supply a low-cost and simplified brushless motor controller that is high in rotor magnetic pole position detection accurately and capable of controlling accurately the corresponding brushless motor as well.

[0009] Still another object of the present invention is to supply a brushless motor controller that can properly control a brushless motor without stopping it, even during a very long interval of flow of a reflux current after power-on switching.

[0010] A further object of the present invention is to minimize position detection errors due to noise.

[0011] A further object of the present invention is to supply a brushless motor controller that can minimize power-on malfunction due to noise.

[0012] A further object of the present invention is to supply a brushless motor controller that can automatically attach importance to more efficient or faster operation during brushless motor operational control.

[0013] A further object of the present invention is to supply a brushless motor controller that covers a more control range.

[0014] A further object of the present invention is to supply appliances, especially an air conditioner, a refrigerator, a washing machine, and a vacuum cleaner, that are powered from the brushless motor thus controlled.

[Disclosure of the Invention]

[0015] A feature of the present invention for achieving the objects described above exists in that the first information signal pattern is stored into an information signal pattern storage means and in that when the first information signal pattern and the third information signal pattern are the same and the second information signal pattern is different from the other two patterns, a reflux current decay signal is generated by an information signal pattern comparison means.

[0016] According to this feature, when the first infor-

mation signal pattern and the third information signal pattern are the same and the second information signal pattern is different from the other two patterns, since a reflux current is generated immediately after commutation and is then decayed, the information signal pattern comparison means compares the first information signal pattern, the second information signal pattern, and the third information signal pattern, and generates a reflux current decay signal. Thus, the loss of the reflux current can be detected. As a result, the position of the rotor can be properly detected immediately after commutation, without providing a rotor position detection inhibition interval, by detecting the loss of the reflux current and then detecting the rotating position of the rotor in accordance with the information signal patterns created by the corresponding information signal creation means. Even if the load changes abruptly, the corresponding brushless motor can also be driven with rapid response since no inhibition time interval needs to be calculated.

[0017] In addition, since rotor position detection is possible without the chopping pattern of any switching device, the position of the rotor can be detected properly, even if the upper or lower three of six switching devices are low in operating speed and inexpensive.

[0018] Another feature of the present invention resides in that the first information signal pattern that has been stored into the above-mentioned information signal pattern storage means is changed to the second information signal pattern by an information signal pattern changing means using a reflux signal decay signal.

[0019] According to this feature, when the first information signal pattern and the third information signal pattern are the same and the second information signal pattern is different from the other two patterns, since a reflux current is generated immediately after commutation and is then decayed and since the second information signal pattern is the information signal pattern corresponding to the rotor position to be detected, the position of the rotor can be properly detected immediately after commutation, without providing a rotor position detection inhibition interval, by detecting from all information signal patterns generated by the information signal creation means, only the information signal pattern matching the second information signal pattern stored within the information signal pattern storage means, and then detecting the rotating position of the rotor in accordance with that detected information signal pattern.

[0020] Still another feature of the present invention resides in that when the fourth information signal pattern matches either of the information signal patterns stored within the information signal pattern storage means, an information signal pattern match signal is generated by the information signal pattern comparison means and the rotating position of the rotor is detected by a rotating position detection means using the information signal pattern match signal.

[0021] According to this feature, when detection of the loss of the reflux current is followed by matching between the fourth information signal pattern and either of the information signal patterns stored within the information signal pattern storage means, since the fourth information signal pattern is the information signal pattern corresponding to the rotor position to be detected, the information signal pattern comparison means compares the fourth information signal pattern and all other information signal patterns stored within the information signal pattern storage means and generates an information signal pattern match signal. Thereby, the rotating position detection means can properly detect the position of the rotor immediately after commutation, without providing a rotor position detection inhibition interval, by detecting the rotating position of the rotor in accordance with the information signal pattern match signal and the corresponding information signal pattern generated by the information signal creation means.

[0022] Still another feature of the present invention resides in that when the required time has elapsed from commutation, the first information signal pattern that was stored into the information signal pattern storage means is changed to the second information signal pattern by the information signal pattern changing means.

[0023] According to this feature, even if the reflux current interval that follows power-on switching is too long for the loss of the reflux current to be detected, the magnetic pole position of the rotor can be detected and the motor can be properly controlled at a low cost.

[0024] A feature of the present invention exists in that for a brushless motor controller that detects the magnetic pole position of the stator from the terminal voltages of the stator coils of each phase and controls the energization (power-on) of these stator coils, the position of the rotor can be detected immediately after commutation, by entering directly into the control circuits of the controller a comparison result information signal obtained through comparison between the detected voltages corresponding to the above-mentioned terminal voltages, and a reference voltage.

[0025] Another feature of the present invention exists in that the position of the rotor can be detected without using the chopping pattern of any switching device.

[0026] Still another feature of the present invention exists in that: the comparison result information signal obtained through comparison between the detected voltages corresponding to the above-mentioned terminal voltages, and a reference voltage, is directly entered into the control circuits, the PWM signal on/off interval is judged in the control circuits, and the delay time for both the PWM signal received from the control circuits and the PWM signal applied to the motor can be set using either an updatable EEPROM, a variable resistor, or the like.

[0027] A further feature of the present invention exists in that the position of the rotor is detected from

the comparison result information signal pattern corresponding to the terminal voltages of the stator coils of multiple phases.

[0028] A further feature of the present invention exists in that the power-on pattern for the stator coils is determined from the comparison result information signal pattern corresponding to the terminal voltages of the stator coils of multiple phases.

[0029] A further feature of the present invention exists in that the interval during which a reflux current flows following power-on switching is detected from the comparison result information signal pattern corresponding to the terminal voltages of the stator coils of multiple phases.

[0030] A further feature of the present invention exists in that the phase signal pattern to be checked for position detection is updated after the reflux current developed through power-on-switching has been lost.

[0031] A further feature of the present invention exists in that when the required time elapses from power-on switching, even if the reflux current interval is very long, next power-on switching can be executed by updating forcibly the signal pattern checked.

[0032] A further feature of the present invention exists in that power-on phase selection is based on either comparison result information, the received phase control command from an external circuit, the contents of the EEPROM, the rotational speed of the motor, or the calculated electrical quantity corresponding to the amount of current flowing into the inverter or motor.

[0033] A further feature of the present invention exists in that in a PWM control region, importance is attached to operational efficiency during phase control, and in a high-speed rotation control region, control is provided to advance the power-on phase.

[0034] A further feature of the present invention exists in that even if the three upper or lower of all six switching devices are low in operating speed and inexpensive, the position of the rotor can be detected properly.

[0035] A further feature of the present invention exists in that a simple position detection software configuration can be included in the control circuits.

[0036] A further feature of the present invention exists in that the size of the data table within the internal position detection software of the control circuits and the occupancy of a RAM or ROM can be minimized.

[0037] And a further feature of the present invention exists in that the brushless motor controlled by such controller as described above can be used as the power supply for an air conditioner, a refrigerator, a washing machine, or a vacuum cleaner.

BRIEF DESCRIPTION OF THE DRAWINGS

[0038]

Figure 1 is a block diagram of the brushless motor controller described in embodiment 1 of the present invention. Figure 2 is a diagram showing the signal waveforms developed at a PWM control current conduction ratio of 100% in embodiment 1. Figure 3 is a diagram showing the signal waveforms developed when the terminal voltages fluctuate near the reference position in embodiment 1. Figure 4 is a chart showing the flow of internal processing by the control circuits in embodiment 1. Figure 5 is a diagram showing the signal waveforms developed at a PWM control current conduction ratio of 100% when upper arm chopping is executed in the inverter circuit of embodiment 1. Figure 6 is a diagram showing the signal waveforms developed when the flow interval of the reflux current that follows power-on switching is very long. Figure 7 is a diagram showing the signal waveforms developed when PWM control is performed with the upper, lower, and first-half 60-degree arm choppers combined in the inverter circuit of embodiment 1. Figure 8 is a diagram showing the signal waveforms developed when PWM control is performed with the upper, lower, and second-half 60-degree arm choppers combined in the inverter circuit of embodiment 1. Figure 9 is a diagram showing the signal waveforms developed when PWM control is performed with the upper, lower, and second-half 30-degree arm choppers combined in the inverter circuit of embodiment 1. Figure 10 is a diagram showing the signal waveforms developed when PWM control is performed with the upper, lower, and first-half 30-degree arm choppers combined in the inverter circuit of embodiment 1. Figure 11 is a diagram showing the operational efficiency of the brushless motor with respect to the power-on phase in embodiment 1. Figure 12 is a diagram showing the speed characteristics of the brushless motor in embodiment 1. Figure 13 is a block diagram of the brushless motor controller described in embodiment 2 of the present invention.

[The Best Embodiment of the Invention]

[0039] The brushless motor controller in embodiment 1 of the present invention is described below. A block diagram of this brushless motor controller is shown as Fig. 1.

[0040] The brushless motor controller in embodiment 1 comprises: rectifying circuit 2 for rectifying the AC voltage supplied from AC power supply 1; smoothing circuit 3 for smoothing the rectifier output voltage of rectifying circuit 2; inverter circuit 4 for converting the output DC voltage of smoothing circuit 3 into an AC volt-

age of any pulse width and supplying this AC voltage to the stator coils of brushless motor 5; terminal voltage detector 8 for sending to the next stage the detected voltage "8a" corresponding to the terminal voltages (= counter-electromotive force) of each phase of the stator coils in brushless motor 5; phase signal creation circuit 9 for creating phase signal "9a" as the magnetic pole position information of the rotor in brushless motor 5 in accordance with detected voltage "8a" mentioned above; EEPROM 10, which contains PWM signal delay time data; and control circuits 6 for controlling the driving of brushless motor 5 in accordance with the data that has been stored into EEPROM 10, speed command signal SO, and the phase signal "9a" created by phase signal creation circuit 9.

[0041] Control circuits 6 can be a single-chip micro-computer or a hybrid IC.

[0042] Phase signal creation circuit 9 compares detected voltage "8a" and a reference voltage and then creates phase signal "9a" for each phase. The reference voltage value is half either the neutral point voltage value of the stator coils in brushless motor 5 or the output DC voltage value of smoothing circuit 3. Even if the characteristics of the power module differ, since the internal constants of software require no modification, versatility can be assigned to the control software by designing the controller so that delay time information can be adjusted using updatable EEPROM 10, an external resistor, or the like.

[0043] Next, control circuits 6 are described in detail below.

[0044] Control circuits 6 have: timer "6j" for sending an ON signal after the elapse of a delay time equivalent to "td" specified in EEPROM 10; PWM signal generation unit "6h" for generating PWM signal 11; data input unit "6i" for reading PWM signal 11, the delay time "td" ON signal, and phase signal "9a" sent from phase signal creation circuit 9, and then sending digital information signal patterns 13; comparison data storage unit "6d" for storing the information signal patterns that have been read in the past; data comparing unit "6g" for comparing newly read information signal patterns 13 and the information signal patterns that have been read in the past, and then sending comparison results 14; phase detection unit "6e" for detecting the phase in accordance with the comparison results 14 received from data comparing unit "6g", and then sending phase detection information 15; speed control unit "6c" for generating power-on pattern 16 based on phase detection information 15 and speed command signal SO; timer "6f" for counting how often signal processing has been repeated during the required electrical angle interval (for example, an electrical angle interval of 30 degrees, an electrical angle interval of 60 degrees, an electrical angle interval of 120 degrees, or an electrical angle interval of 360 degrees, or a mechanical angle interval of 360 degrees); power-on mode counter "6b" for counting power-on mode sessions based on power-on pat-

tern 16 and on the signal processing count output value of timer "6f"; memory "6a" for storing power-on pattern 16 and the power-on mode session count value and supplying power-on pattern 16 to the next stage; and driver 7 for receiving stored power-on pattern 16 from memory "6a" and controlling the switching operation of inverter circuit 4 according to the particular power-on pattern.

[0045] In this embodiment, internal processing by control circuits 6 takes place to control the driving of brushless motor 5 at a PWM control current conduction ratio of 100% as shown in Fig. 2. The signals in Fig. 2 are described first and then internal processing by control circuits 6 is described.

[0046] The signals shown in Fig. 2 are: (a) detected terminal voltage signals "8a" of phases U, V, and W, of the stator coils in brushless motor 5, (b) PWM signal 11 generated by PWM signal generation unit "6h", (c) phase signals "9a" sent from phase signal creation circuit 9 for each phase, (d) information signal patterns 13 sent from data input unit "6i", and (e) phase detection information 15 sent from phase detection unit "6e".

[0047] The upward arrows in Fig. 2 represent the timing in which data input unit "6i" reads phase signals "9a", and part of the timing is shown as "t1" to "t8".

[0048] As shown in Fig. 2, when commutation ① is immediately followed by the occurrence of spike-like voltage 21 at the phase U corresponding to detected voltage "8a", this voltage is incorporated into phase signals "9a", information signal patterns 13, and phase detection information 15. Immediately before commutation ①, the levels of phase signals "9a" were Low, Low, and High (shown for phases U, V, and W, in that order). Likewise, information signal patterns 13 were [0, 0, 1], and phase detection information 15 was Low, Low, and High. Once spike-like voltage 21 has occurred, however, the levels of phase signals "9a" change to High, Low, and High, information signal patterns 13 change to [1, 0, 1], and phase detection information 15 changes to High, Low, and High.

[0049] After that, spike-like voltage 21 disappears from the phase U corresponding to detected voltage "8a", and phase signals "9a" take the same levels (Low, Low, and High) as the signal levels existing immediately before commutation ①. When time further passes, the signal levels of phase signals "9a" change once again to High, Low, and High, at the crossing point of the reference voltage and detected voltage "8a". Information signal patterns 13 sent from data input unit "6i" to data comparing unit "6g" change to [0, 0, 1] at "t1", [1, 0, 1] at "t2", [0, 0, 1] at "t3", and [1, 0, 1] at "t4".

[0050] At this time, the U-, V-, and W-phase signal patterns corresponding to the comparison result information signal "9a" at "t3" are the signal patterns existing immediately before commutation ①, and at the same time, this indicates that the reflux current has been lost as in "t2".

[0051] Data comparing unit "6g" compares informa-

tion signal patterns 13 sent from data input unit "6i", and the past information signal patterns stored within comparison data storage unit "6d". Data comparing unit "6g" compares the information signal patterns 13 obtained at "t1", "t2", and "t3". After the information signal pattern 13 at "t3" has been found to match the signal pattern obtained at "t1" immediately before commutation ①, data comparing unit "6g" judges that the reflux current at "t2" has been lost, and then sends comparison results 14. In accordance with the comparison results 14 that have been received from data comparing unit "6g", phase detection unit "6e" judges that the information signal pattern 13 at "t3" is the signal pattern corresponding to the next phase to be detected, and changes the appropriate information signal pattern within comparison data storage unit "6d" to the information signal pattern 13 existing at "t3".

[0052] For "t4", data comparing unit "6g" compares the information signal pattern 13 existing at "t4" and the information signal pattern of "t2", stored within comparison data storage unit "6d". When both signal patterns match, data comparing unit "6g" sends comparison results 14. In accordance with the comparison results 14 that have been received from data comparing unit "6g", phase detection unit "6e" sends to speed control unit "6c" the phase detection information 15 corresponding to the information signal pattern 13 at "t4".

[0053] After receiving phase detection information 15 from phase detection unit "6e", speed control unit "6c" derives power-on pattern 16 with respect to the stator coils and sends this pattern to driver 7.

[0054] Driver 7, after receiving power-on pattern 16 from speed control unit "6c", drives inverter circuit 4.

[0055] As described above, this embodiment enables the position of the rotor to be properly detected without providing a rotor position detection inhibition time interval.

[0056] Also, although the time corresponding to the particular electrical angle changes with the rotational speed of the motor and thus the prior art makes it necessary to calculate the time corresponding to the electrical angle each time the motor speed changes, no inhibition time interval needs to be calculated in this embodiment. In addition, even if the load changes abruptly, since information signal patterns are created from comparison results on the stator coil terminal voltages and a reference voltage and then before the rotor position corresponding to the information signal pattern is detected, the phase to be detected is confirmed through comparison with the past information signal patterns, the position of the rotor can be detected properly.

[0057] An example of internal processing flow in control circuits 6 is shown as Fig. 4. Internal processing by control circuits 6 consists of: main process 41 for generating the speed control signal of brushless motor 5; position detection process 42 for detecting the position of the rotor; driving process 43 for driving inverter

circuit 4 in accordance with the speed control signal generated in process 41 and with the rotor position detected in process 42; ready flag clearing process 44 for performing main process 41 after executing driving process 43; and match flag clearing process 45.

[0058] Driving process 43 enables power-on switching after the elapse of the required time adjusted during phase correction.

[0059] Next, process 42 is described in detail below.

[0060] During sub-process "42a", timer "6f" counts how often signal processing has been repeated during the required electrical angle interval (for example, an electrical angle interval of 30 degrees, an electrical angle interval of 60 degrees, an electrical angle interval of 120 degrees, or an electrical angle interval of 360 degrees, or a mechanical angle interval of 360 degrees).

[0061] Timer "6f" can also manage the elapse of the required time.

[0062] During sub-process "42b", data input unit "6i" judges whether the PWM signal 11 generated by PWM signal generation unit "6h" is on or off. This sub-process can be simplified by using a flag or a microcomputer for judging the on/off status of the PWM signal.

[0063] During sub-process "42c", data input unit "6i" judges whether a delay time equivalent to the "td" value specified in EEPROM 10 has elapsed. This judgment can be performed by counting with timer "6j" or in sub-process "42a". During this judgment, even if the characteristics of the power module differ, since the internal constants of software require no modification, versatility can be assigned to the control software by designing the controller so that delay time information can be adjusted using EEPROM 10, an external resistor, or the like.

[0064] During sub-process "42d", data input unit "6i" reads the phase signals "9a" corresponding to phases U, V, and W. At this time, output of HI level or LOW level signals from control circuits 6 for the purpose of identifying the timing in which the phase signals "9a" have been read is effective for confirming the operation of the controller.

[0065] During sub-process "42e", timer "6j" judges whether the required time elapsed from power-on switching. This judgment can be performed by counting in sub-process "42a".

[0066] During sub-process "42f", comparison data storage unit "6d" judges whether the required signal patterns for next signal processing have been established. If the required patterns have been established, the ready flag is set to '1' by comparison data storage unit "6d", or if the required patterns have not been established, the ready flag is set to '0'.

[0067] If the setting of the ready flag is '1' in sub-process "42f", comparison data storage unit "6d" sends the established signal patterns to data comparing unit "6g". If the setting of the ready flag is '0' in sub-process

"42f", comparison data storage unit "6d" updates or establishes signal patterns in sub-process "42g" and then after sending these patterns to data comparing unit "6g", changes the setting of the ready flag to '1'.

[0068] During sub-process "42h", comparison data storage unit "6d" clears the match flag used to judge whether the signal patterns have been updated for the first time.

[0069] During sub-process "42j", phase detection unit "6e" checks the information signal patterns of the phase signals "9a" which were read during sub-process "42d", against the signal pattern predetermined by the position of the rotor.

[0070] If, in sub-process "42k", the signal patterns are found to match, control proceeds to sub-process "42m". If the signal patterns are found to mismatch, control skips to sub-process "42l".

[0071] During sub-process "42l", phase detection unit "6e" clears the match flag used to judge whether the signal patterns have matched twice.

[0072] During sub-process "42m", phase detection unit "6e" judges whether the signal patterns have matched twice. If the signal patterns have matched and the match flag is off, phase detection unit "6e" turns the match flag back on during sub-process "42n". If the signal patterns have matched and the match flag is on, control proceeds to sub-process "42o".

[0073] In sub-process "42o", branching occurs to judge whether the signal patterns required for next power-on control processing have been established. If the ready flag is on in sub-process "42o", control proceeds to driving process "43". If the ready flag is off, control proceeds to sub-process "42p".

[0074] If the signal patterns required for next power-on control processing are not established (the ready flag is '0') in sub-process "42o", sub-process "42p" is performed to update/establish these signal patterns. In sub-process "42p", phase detection unit "6e" sets the ready flag to '1' to indicate that the required signal patterns have been updated. In sub-process "42r", phase detection unit "6e" clears the match flag used to judge whether the signal patterns have matched for the first time.

[0075] After the required signal patterns have been updated in sub-process "42g" or sub-process "42p", when the signal patterns of the phase signals "9a" which were read during sub-process "42d", the appropriate power-on pattern for the particular rotating position is determined and driving process "43" is performed.

[0076] Since sub-processes "42f" to "42l" and sub-processes "42o" to "42r" are equivalent, subroutining makes it possible not only to minimize increases in program size, but also to control the brushless motor properly even when the reflux current interval that follows power-on switching is very long.

[0077] Shown in Fig. 5 are: detected terminal voltages "8a" of the U-, V-, and W-phases of the stator coils

in brushless motor at a current conduction ratio less than 100% during PWM control with upper arm chopping in inverter 4; the corresponding PWM signals; the comparison result information signals of each phase that are sent from the comparing circuit; the PWM-on information signal patterns read by control circuits 6; and the position detection information recognized inside the control circuits.

[0078] When control processing that uses the algorithm shown in Fig. 4 is executed seeing Fig. 5, it is resultingly possible not only to prevent mis-judgment, even if, as denoted by "t1" and "t3" in Fig. 5, phase signals equivalent to those of "t2" and "t4" appear immediately after power-on pattern switching, but also to obtain the proper phase signals without suffering any effects of the reflux current flowing immediately after power-on pattern switching, and thus execute power-on switching properly.

[0079] Also, after the signal patterns have been updated in sub-processes "42g" and "42p" described seeing Fig. 4, if the corresponding signals fluctuate near the reference position as shown in Fig. 3 (b), these signals will appear as shown in Fig. 3 (c), and then when control is transferred from process "41" to periodic process "42", process "42" will be performed in the timing of Fig. 3 (d). After this, sub-process "42d" will be performed in the timing of Fig. 3 (e), then signal pattern checking will occur in sub-process "42j", and in sub-process "42k", control will advance from pattern match confirmation to sub-process "42m". At this time, since pattern matching is the first in the present power-on interval and the match flag is off, control will branch from sub-process "42m" into sub-process "42n". Hereafter, sub-process "42d" will be performed once again, but this time, in the "td" timing of Fig. 3 (g), and when sub-process "42j" is performed thereafter, since the signal patterns will not match in sub-process "42k", control will branch into sub-process "42l", where the match flag will then be cleared to return control to process "41".

[0080] When control is further transferred from process "41" to periodic process "42", sub-process "42d" will be performed in the "tc" timing of Fig. 3 (c), then as with the above-mentioned processing sequence, processing will be executed to sub-process "42n", and during the time interval up to this step, sub-processes "42d" to "42m" will be performed. Since the match flag at this time is on, control will further advance to process 43 through sub-process "42o" and the driving process appropriate for the particular position of the rotor will be performed.

[0081] The use of the phase signal creation circuit 9 and position detection algorithm described above enables proper detection of the rotor position ... even if any pulse-like noise occurs ... and hence, proper control of the motor. Although this embodiment assumes that before control can be advanced to the driving process, phase signal "9a" pattern matching must be repeated twice, this embodiment is also valid in any other cases

of multiple times of matching. In addition, this embodiment is valid even if pattern matching is omitted by suppressing the noise and/or signal fluctuations appearing as the terminal voltages of the stator coils in brushless motor 5.

[0082] The terminal voltages "8a" detected when the interval during which the reflux current flows following power-on pattern switching is very long, the comparison result information signals sent from the comparing circuit, and one phase of position detection information inside the control circuits are shown in Fig. 6.

[0083] When this position detection algorithm is used, since phase signal creation circuit 9 reads PWM signal-on phase signals in addition to requiring only a comparator circuit, the same position detection information can be obtained, regardless of whether any choppers are active during PWM control, and thus the motor can be controlled properly, even during PAM control.

[0084] In addition, even when, as shown in Fig. 6, the interval during which the reflux current flows following power-on pattern switching is very long and information signal voltages do not change near their reference position, since sub-process "42e" is provided, the signal patterns to be checked are forcibly modified after the elapse of the required time following power-on switching has been confirmed. Thereby, next power-on switching can be executed without stopping the motor, with the result that the motor can be controlled properly.

[0085] Furthermore, in a configuration using an output variable type of rectifying circuit 2, since the reference voltage of the comparing circuit is variable according to the particular output voltage, this embodiment also enables the same position detection information to be obtained from phase signals during either a PWM control full-region/PAM control mode or a PWM/PAM switching control mode, thus enabling the implementation of proper motor control.

[0086] Detection errors due to noise can also be reduced since control circuits 6 detect (judge) the rotor position in accordance with the phase signal patterns corresponding to the detected terminal voltages of each phase of the stator coils in specific timing.

[0087] In addition, malfunction due to noise can be minimized since control circuits 6 can determine the next power-on pattern from the particular rotor position and the present power-on pattern for the stator coils.

[0088] Furthermore, the use of this algorithm enables not only the configuration of the software to be simplified, but also the size of the data table required for microcomputer control and the related occupancy of a RAM or ROM to be minimized since judgment data on the loss of the reflux current and judgment data on position detection can be the same. Accordingly, proper motor control can be achieved using even a small-capacity low-cost microcomputer, and the incorporation of such a controller into an electrical household appliance can guarantee high product quality at a low cost.

[0089] Those voltage detection signals, PWM sig-

nals, comparison result information signals, PWM signal-on information signal patterns, and position detection information signal waveforms inside the control circuits, that are developed when PWM control is performed with the upper, lower, and first-half 60-degree arm choppers combined in inverter circuit 4, are shown in Fig. 7. Similarly, the above-mentioned five items obtained when PWM control is performed with the upper, lower, and second-half 60-degree arm choppers combined in inverter circuit 4, when PWM control is performed with the upper, lower, and second-half 30-degree arm choppers combined in inverter circuit 4, and when PWM control is performed with the upper, lower, and first-half 30-degree arm choppers combined in inverter circuit 4, are shown in Figs. 8, 9, and 10, respectively.

[0090] In all cases, the same position detection information can be obtained from PWM signal-on comparison result information signals.

[0091] Irrespective of the chopping scheme applied to PWM control, therefore, proper motor control can be implemented under free combinations of the upper arm chopper, the upper and lower arm choppers, the first-half 60-degree chopper, the second-half 60-degree chopper, the first-half 30-degree chopper, and/or the second-half 30-degree chopper, in inverter 4.

[0092] In addition, since, irrespective of the chopping scheme applied to PWM control, the position of the rotor in the motor can be properly detected using this position detection method, only the upper or lower switching devices among all six devices do not need to execute chopping, and this enables a motor controller to be constructed using an inexpensive power module that contains devices low in operating speed and in price. Resultingly, a high-quality motor controller can be realized at a low cost.

[0093] The operational efficiency of a brushless motor with respect to the power-on phase is shown in Fig. 11. Since the operational efficiency of a brushless motor changes according to the power-on phase with respect to counter-electromotive force, the power-on phase is a very important factor. To ensure maximum efficiency during the start of the motor, therefore, the brushless motor can be operated with high efficiency by controlling the power-on phase in accordance with RAM- or ROM-prestored information, the rotational speed of the motor, and the information calculated from the amount of current flowing through the inverter circuit or from the amount of motor current.

[0094] Also, the brushless motor can be operated at the user side during the motor-fitting power-on phase by enabling external control of the power-on phase. The A/D conversion terminals, communications terminals, or input ports of control circuits 6 can be used as the control terminals for such external control.

[0095] During PWM control, by which the speed of the brushless motor is controlled by controlling the pulse widths of the terminal voltage signals supplied to

the stator coils, when the current conduction ratio arrives at its maximum value of 100%, control for a further increased motor speed cannot be provided. During PAM control, by which the motor speed is controlled by controlling the pulse heights of the terminal voltage signals supplied to the stator coils, when the maximum allowable terminal voltage is reached, control for a further increased motor speed cannot be provided. However, the motor speed can be varied by, as shown in Fig 12, changing the power-on phase after maintaining at the same value the terminal voltages supplied to the stator coils. And this method of power-on phase control can be implemented using phase signals.

[0096] The rotational speed of the brushless motor can therefore be controlled over a wide range by performing power-on phase control in addition to the PWM control and PAM control schemes based on the stator coil currents of the motor. For example, when normal mode of operation is to be maintained, operational control characteristics with importance being attached to efficiency can be obtained by providing power-on phase control for maximum motor efficiency under the status that the maximum allowable current conduction ratio is not reached in PWM control or under the status that the maximum allowable supply voltage is not reached in PAM control, and when faster rotation is required, operational control characteristics with importance being attached to speed can be obtained by controlling the power-on phase so as to advance beyond the maximum efficiency point after the maximum allowable current conduction ratio or supply voltage has been reached. This means that since the operational control characteristics of the brushless motor can be obtained with importance being attached to efficiency or speed, the motor can be controlled over a wide range.

[0097] A block diagram of a brushless motor controller using a variable resistor, instead of EEPROM 10 including delay time information, is shown as Fig. 13. When only delay time information is to be stored into EEPROM 10, a simple, low-cost, and high-quality motor controller can be constructed by entering information via a variable resistor or the like.

[0098] Such a controller can be reduced in the number of components required and becomes easier to operate, by constructing the controller as either a hybrid IC chip composed by control circuits 6 and phase signal creation circuit 9, or an intelligent power module consisting of inverter circuit 4, control circuits 6, driver 7, and phase signal creation circuit 9.

[0099] Since the heat pump type of air conditioner changes in conditioning output level according to the particular rotational speed of the compressor, air conditioning can be achieved with high conditioning capabilities by using as the drive for the compressor/blower the brushless motor provided with power-on phase control in addition to PWM control and PAM control as described heretofore. Such an air conditioner can also be improved into an energy-saving type by controlling

its operation in normal operational region with importance being attached to efficiency.

[0100] Similarly, a refrigerator with excellent refrigerating capabilities can be realized by applying as the drive for the compressor/blower the brushless motor controlled using this controller.

[0101] Likewise, a washing machine excellent in controllability can be realized by constructing the washing machine whose pulsator and spin basket are rotated using the brushless motor controlled by this controller.

[0102] Furthermore, a vacuum cleaner excellent in vacuum attraction force can be realized by applying as the drive for the blower of the cleaner the brushless motor controlled using this controller.

[0103] Furthermore, the use of the phase signal creation circuit and position detection algorithm covered by the present invention makes it unnecessary to establish large circuit composition including general-purpose logic circuits, or to use electrolytic capacitors large in capacity. Accordingly, it is possible to implement compact and inexpensive inverter control circuit composition by integrating an inverter circuit and a driver circuit, and to realize a compact, inexpensive, and highly controllable air conditioner, refrigerator, washing machine, or vacuum cleaner, by introducing such inverter control circuit composition.

[0104] According to the present invention, when the first information signal pattern and the third information signal pattern are the same and the second information signal pattern is different from the other two patterns, since a reflux current is generated immediately after commutation and is then decayed, the information signal pattern comparison means compares the first information signal pattern, the second information signal pattern, and the third information signal pattern, and generates a reflux current decay signal. Thus, the loss of the reflux current can be detected. As a result, the position of the rotor can be properly detected immediately after commutation, without providing a rotor-position detection inhibition interval, by detecting the loss of the reflux current and then detecting the rotating position of the rotor in accordance with the information signal patterns created by the information signal creation means. Even if the load changes abruptly, the corresponding brushless motor can also be driven with rapid response since no inhibition time interval needs to be calculated.

[0105] In addition, since rotor position detection is possible without the chopping pattern of any switching device, the position of the rotor can be detected properly, even if the upper or lower three of six switching devices are low in operating speed and inexpensive.

[0106] According to the present invention, when the first information signal pattern and the third information signal pattern are the same and the second information signal pattern is different from the other two patterns, since a reflux current is generated immediately after commutation and is then decayed and since the second

information signal pattern is the information signal pattern corresponding to the rotor position to be detected, the position of the rotor can be properly detected immediately after commutation, without providing a rotor position detection inhibition interval, by detecting from all information signal patterns generated by the information signal creation means, only the information signal pattern matching the second information signal pattern stored within the information signal pattern storage means, and then detecting the rotating position of the rotor in accordance with that detected information signal pattern.

[0107] According to the present invention, when detection of the loss of the reflux current is followed by matching between the fourth information signal pattern and either of the information signal patterns stored within the information signal pattern storage means, since the fourth information signal pattern is the information signal pattern corresponding to the rotor position to be detected, the information signal pattern comparison means compares the fourth information signal pattern and all other information signal patterns stored within the information signal pattern storage means and generates an information signal pattern match signal. Thereby, the rotating position detection means can properly detect the position of the rotor immediately after commutation, without providing a rotor position detection inhibition interval, by detecting the rotating position of the rotor in accordance with the information signal pattern match signal and the corresponding information signal pattern generated by the information signal creation means.

[0108] According to the present invention, even if the reflux current interval that follows power-on switching is too long for the loss of the reflux current to be detected, the magnetic pole position of the rotor can be detected and the motor can be properly controlled at a low cost.

[0109] According to the present invention, it is possible not only to detect the position of the rotor in a brushless motor immediately after power-on switching, but also to detect the magnetic pole position of the rotor, even if the reflux current interval that follows power-on switching is very long, and thus the motor can be controlled at a low cost and with high accuracy. In addition, position detection errors and power-on malfunction due to noise can be minimized and the control range can be expanded. Furthermore, the brushless motor can be controlled over a wide range since motor operation can be controlled with importance being attached to efficiency or speed.

[0110] And a high-performance air conditioner, refrigerator, washing machine, or vacuum cleaner can be realized by using as their drive the brushless motor controlled by the controller described heretofore.

[0111] The use of comparator signals enables highly accurate motor control to be achieved in PWM control full-region mode, PAM control mode; and

PWM/PAM switching control mode, by updating position detection signal patterns after the PWM signal-on reflux current following power-on switching has been lost, and then checking the new position detection signal patterns against the information within the control circuits. Also, an air conditioner, refrigerator, washing machine, or vacuum cleaner excellent in controllability can be realized by constructing these appliances with the motor controlled by this motor controller, as their drives.

[Industrial Applicability]

[0112] As described above, the brushless motor controller covered by the present invention, and appliances using this controller can be used to control the rotational speed of a brushless motor to the desired speed. This controller is therefore suitable for use in: an air conditioner that conditions interior air by controlling its internal compressor/blower driving brushless motor using the controller; a refrigerator that provides refrigeration by controlling its internal compressor/blower driving brushless motor using the controller; a washing machine that washes clothes by controlling its pulsator or spin-basket driving brushless motor using the controller; and a vacuum cleaner that cleans rooms by controlling its blower driving brushless motor using the controller.

Claims

1. A brushless motor controller having an information signal generation means for generating the information signal patterns corresponding to the terminal voltages of the stator coils of multiple phases in a brushless motor, a rotating position detection means for detecting the rotating position of the rotor in said brushless motor in accordance with said information signal patterns, and a power-on control unit for supplying power to said stator coils in accordance with said rotating position, wherein said controller is characterized in that it further has

an information signal pattern storage means for storing said information signal patterns, and an information signal pattern comparison means by which the first information signal pattern stored within said information signal pattern storage means, the second information signal pattern generated immediately after commutation, and the third information signal pattern generated after the elapse of the required time immediately following said commutation are compared and when said first information signal pattern and said third information signal pattern are the same and said second information signal pattern is different from said first information signal pattern and said third information signal pattern, a reflux

current decay signal is generated to indicate that the reflux current has been decayed.

2. Such brushless motor controller as set forth in Claim 1 above, wherein said controller is characterized in that it further has an information signal pattern changing means by which said first information signal pattern stored within said information signal pattern storage means is changed to said second information signal pattern in accordance with said reflux current decay signal.
3. Such brushless motor controller as set forth in Claim 1 above, wherein said motor controller is characterized in that when matching is established between the stored information signal pattern within said information signal pattern storage means and the fourth information signal pattern generated after the required time elapsed from the occurrence of said third information signal pattern, said information signal pattern changing means generates an information signal pattern match signal, and in that said rotating position detection means detects the rotating position of the rotor in accordance with said information signal pattern match signal.
4. Such brushless motor controller as set forth in Claim 2 above, wherein said information signal pattern changing means is characterized in that when the required time elapses from commutation, said first information signal pattern stored within said information signal pattern storage means is changed to said second information signal pattern.
5. A brushless DC motor controller having a voltage detection means capable of generating the detected voltage values corresponding to the terminal voltages of the stator coils of multiple phases in a brushless motor, a reference voltage generation means for generating a reference voltage, a comparison means capable of generating a comparison result information signal after comparing said detected voltages and reference voltage, and a control means for detecting the rotating position of the rotor in the brushless motor in accordance with the foregoing comparison result information signal and then sending the appropriate power-on signal to said stator coils according to the detected rotating position, wherein said brushless DC motor controller is characterized in that said control means detects the rotor position immediately after power-on switching for said stator coils without an inhibition time interval being provided.
6. A brushless DC motor controller having a rectifying circuit for transforming an AC supply voltage into a DC voltage, an inverter circuit for converting said

DC voltage into an AC voltage and supplying this AC voltage to a brushless motor, and control circuits for controlling the inverter circuit, wherein said brushless DC motor controller is characterized in that it further has a voltage detection means capable of generating the detected voltage values corresponding to the terminal voltages of the stator coils of multiple phases in said brushless motor, a reference voltage generation means for generating a reference voltage, a comparison means capable of generating a comparison result information signal after comparing said detected voltages and reference voltage, and a control means for detecting the rotating position of the rotor in the brushless motor in accordance with the foregoing comparison result information signal and then sending the appropriate power-on signal to said stator coils according to the detected rotating position, and in that said control means detects the rotor position immediately after power-on switching for said stator coils without an inhibition time interval being provided.

7. A brushless DC motor controller having converter circuits composed of a rectifying circuit for transforming an AC supply voltage into a DC voltage and a chopper circuit for controlling the magnitude of said DC voltage, an inverter circuit for receiving an DC voltage from said converter circuits and then after converting this voltage into an AC voltage, supplying this AC voltage to a brushless motor, a converter control circuit for controlling the switching operation of said chopper circuit, an inverter control circuit for controlling the switching operation of said inverter circuit and driving the brushless motor, and control circuits for controlling said converter control circuit and inverter control circuit, wherein said brushless DC motor controller is characterized in that it further has a voltage detection means capable of generating the detected voltage values corresponding to the terminal voltages of the stator coils of multiple phases in said brushless motor, a reference voltage generation means for generating a reference voltage, a comparison means capable of generating a comparison result information signal after comparing said detected voltages and reference voltage, and a control means for detecting the rotating position of the rotor in the brushless motor in accordance with the foregoing comparison result information signal and then sending the appropriate power-on signal to said stator coils according to the detected rotating position, and in that said control means detects the rotor position immediately after power-on switching for said stator coils without an inhibition time interval being provided.
8. A brushless motor controller having a voltage detection means capable of generating the detected voltage values corresponding to the terminal

nal voltages of the stator coils of multiple phases in a brushless motor, a reference voltage generation means for generating a reference voltage, a comparison means capable of generating a comparison result information signal after comparing said detected voltages and reference voltage, a control means for detecting the rotating position of the rotor in the brushless motor in accordance with the foregoing comparison result information signal and then sending the appropriate power-on signal to said stator coils according to the detected rotating position, and an output means for using the above-mentioned power-on signal to supply power to said stator coils, wherein said brushless motor controller is characterized in that said control means detects the rotor position in accordance with the comparison result information signal patterns of multiple phases.

9. A brushless motor controller having a voltage detection means capable of generating the detected voltage values corresponding to the terminal voltages of the stator coils of multiple phases in a brushless motor, a reference voltage generation means for generating a reference voltage, a comparison means capable of generating a comparison result information signal after comparing said detected voltages and reference voltage, a control means for detecting the rotating position of the rotor in the brushless motor in accordance with the comparison result information signal received from said comparison means and generating a power-on signal, and an output means for using this power-on signal to supply power to said stator coils, wherein said brushless motor controller is characterized in that said control means determines the power-on pattern for said stator coils in accordance with the comparison result information signal patterns of multiple phases.
10. A brushless motor controller having a voltage detection means capable of generating the detected voltage values corresponding to the terminal voltages of the stator coils of multiple phases in a brushless motor, a reference voltage generation means for generating a reference voltage, a comparison means capable of generating a comparison result information signal after comparing said detected voltages and reference voltage, a control means for detecting the rotating position of the rotor in the brushless motor in accordance with the above-mentioned comparison result information signal and sending the appropriate power-on signal to the stator coils according to the detected rotor position, and an output means for using the above-mentioned power-on signal to supply power to said stator coils, wherein said brushless motor controller is characterized in that said control means uses

said comparison result information signal patterns to detect the interval during which the reflux current that follows power-on switching is flowing.

11. A brushless motor controller having a voltage detection means capable of generating the detected voltage values corresponding to the terminal voltages of the stator coils of multiple phases in a brushless motor, a reference voltage generation means for generating a reference voltage, a comparison means capable of generating a comparison result information signal after comparing said detected voltages and reference voltage, a control means for obtaining phase signals in accordance with the above-mentioned comparison result information signal and then after detecting the position of the rotor in accordance with the obtained phase signals, generating the appropriate power-on signal, and an output means for using the above-mentioned power-on signal to supply power to said stator coils, wherein said brushless motor controller is characterized in that the phase signal patterns to be checked for position detection are updated after the loss of the reflux current which follows power-on switching.
12. A brushless motor controller having a voltage detection means capable of generating the detected voltage values corresponding to the terminal voltages of the stator coils of multiple phases in a brushless motor, a reference voltage generation means for generating a reference voltage, a comparison means capable of generating a comparison result information signal after comparing said detected voltages and reference voltage, a control means for detecting the rotating position of the rotor in the brushless motor in accordance with the above-mentioned comparison result information signal and sending the appropriate power-on signal to the stator coils according to the detected rotor position, and an output means for using the above-mentioned power-on signal to supply power to said stator coils, wherein said brushless motor controller is characterized in that after the elapse of the required time from power-on switching, said control means updates the phase signal patterns to be checked for position detection.
13. A brushless motor controller having a voltage detection means capable of generating the detected voltage values corresponding to the terminal voltages of the stator coils of multiple phases in a brushless motor, a reference voltage generation means for generating a reference voltage, a comparison means capable of generating a comparison result information signal after comparing said detected voltages and reference voltage, a control means for detecting the rotating position of the rotor

in the brushless motor in accordance with the above-mentioned comparison result information signal and sending the appropriate power-on signal to the stator coils according to the detected rotor position, and an output means for using the above-mentioned power-on signal to supply power to said stator coils, wherein said brushless motor controller is characterized in that delay time information on transfer from said control means to the brushless motor is stored into an updatable ROM by said control means.

14. A brushless motor controller having a voltage detection means capable of generating the detected voltage values corresponding to the terminal voltages of the stator coils of multiple phases in a brushless motor, a reference voltage generation means for generating a reference voltage, a comparison means capable of generating a comparison result information signal after comparing said detected voltages and reference voltage, a control means for detecting the rotating position of the rotor in the brushless motor in accordance with the above-mentioned comparison result information signal and sending the appropriate power-on signal to the stator coils according to the detected rotor position, and an output means for using the above-mentioned power-on signal to supply power to said stator coils, wherein said brushless motor controller is characterized in that said control means is constructed so that delay time information on transfer from said control means to the brushless motor will be supplied via a variable resistor.

15. A brushless motor controller having a voltage detection means capable of generating the detected voltage values corresponding to the terminal voltages of the stator coils of multiple phases in a brushless motor, a reference voltage generation means for generating a reference voltage, a comparison means capable of generating a comparison result information signal after comparing said detected voltages and reference voltage, a control means for detecting the rotating position of the rotor in the brushless motor in accordance with the above-mentioned comparison result information signal and sending the appropriate power-on signal to the stator coils according to the detected rotor position, and an output means for using the above-mentioned power-on signal to supply power to said stator coils, wherein said brushless motor controller is characterized in that said control means detects the position of the rotor in accordance with said comparison result information signal patterns and switches the power-on phase in accordance with memory-stored power-on phase information.

16. A brushless motor controller having a voltage

detection means capable of generating the detected voltage values corresponding to the terminal voltages of the stator coils of multiple phases in a brushless motor, a reference voltage generation means for generating a reference voltage, a comparison means capable of generating a comparison result information signal after comparing said detected voltages and reference voltage, a control means for detecting the rotating position of the rotor in the brushless motor in accordance with the above-mentioned comparison result information signal and sending the appropriate power-on signal to the stator coils according to the detected rotor position, and an output means for using the above-mentioned power-on signal to supply power to said stator coils, wherein said brushless motor controller is characterized in that said control means detects the position of the rotor in accordance with said comparison result information signal patterns and switches the power-on phase in accordance with external phase control commands.

17. Such brushless motor controller as set forth in Claim 10 above, wherein said motor controller is characterized in that it uses either A/D conversion terminals, communications terminals, or input ports, as the input terminals for receiving external phase control commands.

18. A brushless motor controller having a voltage detection means capable of generating the detected voltage values corresponding to the terminal voltages of the stator coils of multiple phases in a brushless motor, a reference voltage generation means for generating a reference voltage, a comparison means capable of generating a comparison result information signal after comparing said detected voltages and reference voltage, a control means for detecting the rotating position of the rotor in the brushless motor in accordance with the above-mentioned comparison result information signal and sending the appropriate power-on signal to the stator coils according to the detected rotor position, and an output means for using the above-mentioned power-on signal to supply power to said stator coils, wherein said brushless motor controller is characterized in that said control means performs phase control in a PWM control region with importance being attached to operational efficiency and performs power-on phase advancement control in the control region with importance being attached to high-speed rotation.

19. Such brushless motor controller as set forth in either Claim from 5 to 10 above, wherein said control means is characterized in that it is composed of a microcomputer having a plurality of input/output ports.

20. Such brushless motor controller as set forth in either Claim from 5 to 18 above, wherein said control means is characterized in that it is composed of a microcomputer capable of judging at least whether the PWM signal is on or off. 5
21. Such brushless motor controller as set forth in either Claim from 5 to 18 above, wherein said control means is characterized in that it is composed of a hybrid IC having a plurality of input/output ports. 10
22. Such brushless motor controller as set forth in either Claim from 5 to 18 above, wherein said control means is characterized in that it is composed of a hybrid IC capable of judging at least whether the PWM signal is on or off. 15
23. Such brushless motor controller as set forth in either Claim from 5 to 22 above, wherein said control means is characterized in that it sends signals in almost the same timing as said phase signals are read. 20
24. An air conditioner characterized in that it is constructed using a compressor and blower driven by a brushless motor whose operation is controlled by such brushless motor controller as set forth in either Claim from 5 to 22 above. 25
25. A refrigerator characterized in that it is constructed using a compressor and blower driven by a brushless motor whose operation is controlled by such brushless motor controller as set forth in either Claim from 5 to 22 above. 30
26. A washing machine characterized in that it is constructed using as its drive a brushless motor whose operation is controlled by such brushless motor controller as set forth in either Claim from 5 to 22 above. 35 40
27. A vacuum cleaner characterized in that it is constructed using as its drive a brushless motor whose operation is controlled by such brushless motor controller as set forth in either Claim from 5 to 22 above. 45

50

55

FIG. 1




FIG. 2




FIG. 3




FIG. 5




FIG. 4




FIG. 6




FIG. 7




FIG. 9





FIG. 10




FIG. 13




FIG. 11





FIG. 12



INTERNATIONAL SEARCH REPORT

International application No.

PCT/JP99/03658

A. CLASSIFICATION OF SUBJECT MATTER Int.Cl. ⁶ H02P6/16		
According to International Patent Classification (IPC) or to both national classification and IPC		
B. FIELDS SEARCHED		
Minimum documentation searched (classification system followed by classification symbols) Int.Cl. ⁶ H02P6/14-6/18		
Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched Jitsuyo Shinan Koho 1926-1995 Toroku Jitsuyo Shinan Koho 1994-1999 Kokai Jitsuyo Shinan Koho 1971-1994 Jitsuyo Shinan Toroku Koho 1996-1999		
Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)		
C. DOCUMENTS CONSIDERED TO BE RELEVANT		
Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	JP, 5-236787, A (Fujitsu General Ltd.), 10 September, 1993 (10. 09. 93), Page 3, right column, line 32 to page 4, right column, line 44 (Family: none)	1-12, 15-17, 19-27
X	JP, 7-135794, A (Sanyo Electric Co., Ltd.), 23 May, 1995 (23. 05. 95), Page 3, right column, line 50 to page 4, left column, line 29 (Family: none)	13, 19-27
X	JP, 63-154093, A (Canon Inc.), 27 June, 1988 (27. 06. 88), Page 2, lower left column, line 11 to page 3, upper left column, line 20 (Family: none)	14, 19-27
X	JP, 4-334994, A (Seiko Seiki K.K.), 24 November, 1992 (24. 11. 92), Page 3, right column, line 48 to page 4, right column, line 23 (Family: none)	18-27
<input checked="" type="checkbox"/> Further documents are listed in the continuation of Box C. <input type="checkbox"/> See patent family annex.		
* Special categories of cited documents: "A" document defining the general state of the art which is not considered to be of particular relevance "E" earlier document but published on or after the international filing date "L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified) "O" document referring to an oral disclosure, use, exhibition or other means "P" document published prior to the international filing date but later than the priority date claimed "T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention "X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone "Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art "&" document member of the same patent family		
Date of the actual completion of the international search 28 September, 1999 (28. 09. 99)		Date of mailing of the international search report 5 October, 1999 (05. 10. 99)
Name and mailing address of the ISA/ Japanese Patent Office		Authorized officer
Facsimile No.		Telephone No.

Form PCT/ISA/210 (second sheet) (July 1992)

INTERNATIONAL SEARCH REPORT

International application No.

PCT/JP99/03658

C (Continuation). DOCUMENTS CONSIDERED TO BE RELEVANT		
Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	JP, 3-285591, A (Aisin Seiki Co., Ltd., et al.), 16 December, 1991 (16. 12. 91), Page 4, upper left column, line 3 to upper right column, line 12 (Family: none)	18-27

Form PCT/ISA/210 (continuation of second sheet) (July 1992)